

MODEL No.
BP-70I

Compatible with all 14.4V E-Robo series tools
 1.3Ah Capacity



BP-70I Intelligent battery



BP-70I with CH-70DC 1H Charger

FEATURES

"Smart" Replacement Battery

The BP-70I intelligent battery is the same as the BP-70R with the addition of LED display. The LED on the side of the battery allows the user to monitor the status of the battery's total life and power in between charges.

It also allows visual evaluation of battery power while in use.

When not used with the tool, just press the check button to get an instant read-out of charge remaining.

SPECIFICATIONS

Output voltage : 14.4 VDC
 Capacity : 1.3Ah
 Type : Nickel Cadmium
 Charge time :
 15 min with CH-35R or CH-35EMC
 LED indicator : Capacity,
 recharge cycles

SIZE

100 (L) x 137 (H) x 75 (W) mm

WEIGHT

750 g

REMARKS

- * The battery has a limited life. When capacity becomes about 1 / 2 of the original capacity, the battery should be replaced.
- * If the battery is stored without being charged, natural drainage will cause the power to be reduced. Be sure to charge the battery every 3 months.
- * The battery will need to be fully charged before first time use.
- * Remaining battery capacity level To check remaining battery capacity level, press the check button. The remaining battery capacity level is displayed for about 5 seconds. Recharge the battery when the bottom light starts to blink.
- * Charging level While the battery is charged, the indicator lights up as the capacity level increases.
- * Number of charges Keep pressing the check button for 10 seconds to show number of charges performed. LED pattern shows number in binary system.